

Peter Engh®

1011 W. 43rd Street
MPLS., MN 55409

PH: 612-827-7992
FX: 612-827-0198



rV
MODEL
3

Remote Volume Control

The rV3 controls earpiece or headphone volume for live remotes and phone interviews. **IFB situations may be simplified** by using the rV3 instead of battery powered amplifiers. A +4dBm line or active headphone output will easily drive an earpiece or Sony MDR-7506 headphones through this passive attenuator.

FEATURES:

- **No power required;** passive design
- **Compact:** H: 4.5", W: 1.7", D:1.5", 6 oz.
- XLR input, (unbalanced, pin 2 hot)
- Earpiece outputs - mini and 1/4" mono
- Headphone output - 1/4" mono both ears
- Environmentally sealed volume control
- Belt clip - stainless steel
- Durable finish with laser engraved markings

Accessories available:

- #TRXY-12 - Adapter "Y" adapter cable for running two rV3s from a headphone output
- #TSX-1/4" to XLR adapter (not shown)

Application notes:

The rV3 is an excellent accessory to the JK Audio RemoteMix 3 phone interface. Simply feed from the XLR line output or adapt from the headphone jack to XLR. Boost the gain on the JK so a comfortable level may be heard around "7" on the rV3. A Gentner Microtel will run two rV3s from it's headphone output.

